Updating Skycut Firmware

By Sandy McCauley

June 2, 2019

IMPORTANT: Do NOT update unless you have the <u>black</u> background control panel.

(1) Download the UpDate application from the following link:

https://www.iloveknk.com/Support/Software/Skycut/Updater/

- (2) Note that only computers running Windows will be able to install the firmware update. If you do not own a PC, borrow one from a friend. Note that you do not need any other software installed... only this UpDate app and then the firmware update file from the next step.
- (3) Download the latest firmware update file from the following link. Pick which link matches the Skycut model you own:
 - C Series: https://www.iloveknk.com/Support/Software/Skycut/CModel/

D Series: https://www.iloveknk.com/Support/Software/Skycut/DModel/

V Series: https://www.iloveknk.com/Support/Software/Skycut/VModel/

- (4) Connect the Skycut to the computer via a USB cable. This is the only connection that will work with the UpDate. Power on the Skycut and wait for the control panel menu to appear.
- (5) From Windows Explorer, extract the Update.exe file from the zip you downloaded in Step (1). Launch (double click) this file and look for a new icon on your Windows Task Bar:



(6) Click on that icon and the following window should pop up:

WDDate For Sky	Cut V7.120 ⁻	1		-		×
Сом	COM:	COM5 -	Refresh			
C TCP/IP	TCP/IP:	192.168.16.254	PORT 8080	 -		
 USB Printer 			-			
BinFile Path:				 	Open Fil	e
UpDate						

(7) The **USB printer** option should be marked and **PORT** set to 8080. Click on **Open File** and browse to locate the bin file you downloaded in Step (3):

UpDate For SkyCut V7.1201		-		×				
C COM COM:	COM5 Refresh							
C TCP/IP TCP/IP:	192.168.16.254 PORT 8080							
USB Printer	•							
BinFile Path: C:\Users\14804\Google Drive\Skycut from PC\Firmware Updates\C_V110611.bin Open File								
UpDate								

(8) Click on **UpDate** and wait while the firmware is updated. You will see the light on the Skycut shut off but the control panel will display a progress bar. The **UpDate** window will also display a progress bar:

UpDate For SkyCut V7	.1201		_		×		
С сом сом	COM5 Refr	esh					
C TCP/IP TCP/	P: 192.168.16.254	PORT 8080					
C USB Printer ust	#vid_0483&pid_5750#skycut_3759#	•					
BinFile Path: C:\Users\14804\Google Drive\Skycut from PC\Firmware Updates\C_V110611.bin Open File Open File							
	Wait1//1						

(9) The process should only take a minute or less. When completed you will hear the Skycut beep a few times and the head will move back and forth a bit. On the screen the UpDate button will now say OK. <u>IMPORTANT</u>: Do <u>NOT</u> click on this button or the update process will repeat and you will need to wait for it to update a second time. Instead, just close the window by clicking on the little X in the upper right corner:

UpDate For SkyCut V7.1201 - X								
С сом	COM:	COM5	Refresh					
C TCP/IP	TCP/IP:	192.168.16.254	PORT	8080		Click here to close		
BinFile Path: C:\Users\14804\Google Drive\Skycut from PC\Firmware Updates\C_V110611.bin Open File								
			ок ┥		Do NOT click repeat and yo	on OK or update will u'll need to wait.		

(10) You're all set! You can remove the USB cable (if you use an alternative connection method) and proceed to use your Skycut.